



# Hercules MA515.C.CG.001

# Specification

Part No.	MA515.C.CG.001Hercules Heavy Duty Screw Mount Antenna MIMO Single Band 2.4GHz2.4GHz suitable for ISM Bands/ZigBee/WLAN/Bluetooth IEEE.802.11n High Isolation between Antenna Elements UV and vandal resistant PE housing IP67 & IP69K compliance Height 29mm Diameter 49mm RoHS Compliant	
Product Name		
Feature		



# 1. Introduction

MIMO communication systems are needed in high speed wireless applications. A MIMO (Multiple-Input-Multiple-Output) system uses at least two antenna structures and is more advantageous than single-input single-output (SISO) by increasing channel capacity and reducing transmitting power. MIMO antennas should have compact structure, high radiation efficiency, low envelope correlation, and high isolation between the signal ports.

In small structures (antennas spaced closely), the application of MIMO technology has been restricted by high degree of coupling and spatial correlation between antenna elements due to the limited available space.

The isolation between antennas become critical as it can deteriorate the system

performance and decreases channel capacity. Taoglas have designed the Hercules MA515 antenna to meet these demanding requirements

The Hercules MA515 MIMO 2.4GHz 3dBi antenna is low profile, heavy-duty, fully IP67 and IP69K waterproof external M2M antenna for use, transportation and remote monitoring applications. This unique omni-directional 3dBi antenna provide high efficiency and high isolation (>20dB), between antennas elements in a heavy-duty low profile compact structure, delivering powerful MIMO antenna technology for Wi-Fi 802.11n.

The antenna screws down permanently onto a roof or metal panel and can be pole or wall-mounted. The two antenna elements are vertically polarized, matching well with the polarization of most wireless routers antennas. An envelope correlation co-efficiency of only 0.2 ensures good performance with the MIMO module.

For industries such as remote monitoring, smart meter systems, construction equipment, public safety at only 29mm high, the Hercules MA515 MIMO antenna provides an unobtrusive, robust, rugged antenna that is durable even in extreme environments.



# 2. Specification

#### Electrical

	Antenna 1	Antenna 2
Operation Frequency (GHz)	2.4~2.5	2.4~2.5
Polarization	Linear	Linear
Impedance (ohms)	50Ω	50Ω
Min Isolation (dB)	-25	-25
Max VSWR	2.0:1	2.0:1
Max Return Loss (dB)	-10	-10
Peak Gain (dBi)	3.0	3.0
Efficiency (%)	56	56
Average Gain (dB)	-2.5	-2.5
Radiation Properties	Omni - Directional	Omni - Directional
Max Input Power	2W Max	

#### Mechanical

Dimensions (mm)	Height=29mm Diameter=49mm
Cable	1M RG316 - Fully Customizable
Casing	UV Resistant PC
Base and Thread	Nickel plated Zinc Alloy/Steel
Weather proof gasket	CR4305 foam with 3M9448WC double-side adhesive
Connector	RP-SMA Male Fully Customizable
Tread Diameter (mm)	18mm
Sealant	Rubber Stopper

#### Environmental

Protection	IP67 & IP69K
Corrosion	5% NACI for 96hrs- Nickel plated steel base and thread
Temperature Range	-40°C to +85°C
Thermal Shock	100 cycles -40°C to +85°C
Humidity	Non-condensing 65°C 95% RH
Shock (Drop Test)	1M drop on concrete 6 axes

\* The Hercules MA515 MIMO antenna performance was measured with RG316 coaxial cable at 1 meter cable length on a 30x30 cm ground plane.



## 3.1 Test Set-Up




Figure 1. Impedance measurements.



Figure 2. Peak gain, efficiency and radiation pattern measurements.



#### 3.2 Return Loss





Figure 3. Return loss of the Hercules MA515 MIMO antenna from 2100 MHz to 2700 MHz.



## 3.3 VSWR

Figure 4. VSWR of the Hercules MA515 MIMO antenna from 2100 MHz to 2700 MHz.



#### 3.4 Isolation





Figure 5. Isolation of the Hercules MA515 MIMO antenna from 2100 MHz to 2700 MHz

# 3.5 Envelope Correlation Coefficient (ECC)



**Frequency (GHz) Figure 6.** ECC of the Hercules MA515 MIMO antenna from 2300 MHz to 2600 MHz.



#### 3.6 Efficiency





Figure 7. Efficiency of the Hercules MA515 MIMO antenna from 2300 MHz to 2600 MHz.



## 3.7 Peak Gain

Figure 8. Peak Gain of the Hercules MA515 MIMO antenna from 2300 MHz to 2600 MHz.



#### 3.8 Average Gain




Figure 9. Average Gain of the Hercules MA515 MIMO antenna from 2300 MHz to 2600 MHz.

## 3.9 3D Radiation Patterns






Figure 10. 3D Radiation Pattern at 2450 MHz of the MA515 Antenna, a) Antenna 1, b) Antenna 2



# 3.10 2D Radiation Patterns

#### 3.10.1 MIMO Antenna 1 2400 MHz Band









# 3.10 2D Radiation Patterns

#### 3.10.1 MIMO Antenna 1 2400 MHz Band










# 3.10 2D Radiation Patterns


#### 3.10.1 MIMO Antenna 1 2400 MHz Band








## 4. Antenna Drawing





# 5. Installation




Recommended torque for mounting is 95Nm or 70ftlbs Maximum torque for moutning is 135.6Nm or 100ft lbs



Figure 14. Installation



# 6. Packaging



Taoglas makes no warranties based on the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice. Taoglas reserves all rights to this document and the information contained herein. Reproduction, use or disclosure to third parties without express permission is strictly prohibited. Copyright © Taoglas Ltd.